

# On Line UPS PlusPRO 4 3000VA/2700Watt Non Battery



**Kode** : PlusPRO 4-3000  
**Brand** : Aplus  
**Jenis** : UPS  
**Harga** : Rp 10.000.000,00

**PlusPRO 4-3000** adalah UPS **online true double conversion dengan rating 3000VA/2700Watt** yang menghadirkan **output pure sinewave** dengan **waktu perpindahan nol (zero transfer time)**. Dirancang fleksibel dalam satu perangkat yang dapat digunakan sebagai **rack-mount** maupun **tower**, seri ini memberikan perlindungan daya tingkat profesional.

**\*Penjualan produk ini tidak termasuk battery**

Penawaran Harga Spesial

 **08112039555**

## Features :

- Intelligent Slot (SNMP) + USB multiple communications included
- High performance true double conversion On Line UPS 1-3KVA
- External battery bank to extend back-up time (Optional)
- Microprocessor control guarantees high reliability
- Low heat dissipation in long time operation
- RS-232 port multiple communications
- High efficiency mode (ECO mode)
- Output voltage regulation +/-1%
- Automatic self-testing function
- Power management software
- Output power factor 0.9
- Wide input range
- Fan speed control
- DC start





### Battery Type :

- VRLA 12V/7AH atau 12V/9AH
- 6 pcs
- Rated Battery Voltage 72VDC
- **Battery dimension 151 x 65 x 100 mm**

Extend Battery Box :  
**Battery Box BBR2B-96V Maksimal 6 battery (72VDC)**

### Specification :

INPUT	
<b>Voltage</b>	1 Phase 2 Wires with Ground 220/230/240Vac
<b>Voltage Range</b>	110-300Vac
<b>Frequency</b>	50Hz or 60Hz (Auto-Sensing)
<b>Type of Connection</b>	IEC-320 C20 connection & EU plug power cable
OUTPUT	
<b>Voltage</b>	220/230/240Vac
<b>Voltage Range</b>	+/- 1%
<b>Frequency (Battery Mode)</b>	50Hz or 60Hz +/- 0.05Hz

<b>Waveform</b>	Pure Sinewave
<b>THD</b>	<2%(linear load)
<b>Crest Ratio</b>	3:1
<b>EFFICIENCY</b>	
<b>Inverter Mode</b>	>90%
<b>BATTERY</b>	
<b>Voltage</b>	72VDC
<b>Type</b>	VRLA 12V/7AH *6pcs or 12V/7AH *6pcs
<b>Recharge Time</b>	5 hours to 90%
<b>External Battery Connectors</b>	72VDC
<b>TRANSFER TIME</b>	
<b>Battery Mode to Inverter Mode</b>	0ms
<b>Inverter to Bypass</b>	<4ms
<b>DISPLAY</b>	
<b>LCD Display</b>	Input, Output, Load, Battery, Mode/Fault/Warning code, Inverter operating, Bypass operating, Output voltage and frequency and Bypass disable/enable selection information
<b>AUDIBLE ALARM</b>	
<b>Battery Mode</b>	Beeps Every 4 Seconds
<b>Low Battery</b>	Sounding Every Second
<b>Overload</b>	Sounding Twice Every Second
<b>Fault</b>	Beeping continuously
<b>COMMUNICATIONS</b>	
<b>Interface (Port)</b>	RS-232
<b>USB Port</b>	Yes
<b>Intelligent Slot (SNMP port)</b>	Yes

<b>SNMP Card</b>	SNMP MINI card
<b>ENVIRONMENT</b>	
<b>Operating Temperature</b>	0°C-40°C
<b>Humidity</b>	<95% (Non-condensing)
<b>Acoustic Noise</b>	<50db at 1M
<b>PHYSICAL</b>	
<b>Rack Height</b>	Tower/Rack: 2U
<b>Dimension (W*D*H)</b>	568*440*88(2U)mm

Manual :

[PlusPro4-3000/2700 Manual](#)

Brochure :

[PlusPro4-3000/2700 Brochure](#)

Battery Installation Guide :

[Aplus\\_Plus\\_battery\\_Installation.pdf](#)

*\* Harga, spesifikasi, dan ketersediaan bisa berubah dan tidak mengikat*

**URL :** <https://www.citraweb.com/produk/1435/>

**Informasi lebih lanjut, pemesanan dan pembelian, hubungi: 0274-554444 atau email [sales@citraweb.com](mailto:sales@citraweb.com)**